

MBX5540LTE

Multiband amplifier



4-input (III+DAB, IV, V, UHF) multiband TV indoor amplifier with 31dB gain and up to 125dB μ V output level on UHF band, separate amplification with independent level adjustment (20dB) for each input and low noise figure. 790MHz 4G LTE integrated filter.

Technical Chars

- The high gain and high output level make it ideal for use in medium to large centralised systems.
- **High shielding against LTE noise (LTE Free)** thanks to **die-cast ZAMA** chassis with F-connectors and metal cover with **captive screws** covering the amplification section.
- Adjustments on the inside, under the cover, to **prevent tampering** by third parties.
- -30dB test socket available on all models.
- Jumpers for inserting **remote power supply** on all inputs (100mA total), self-resetting **short-circuit protection** system and power supply status LED.
- **High-performance, low-power switching power supply.**
- Clamp for connection of TV system earth.

initial_fields		
Code		235109
Input no.		4
Inputs		III+DAB, IV, V, UHF
DAB, III Frequency	MHz	174 - 230
Frequency IV	MHz	470 - 606
V Frequency	MHz	606 - 790
Frequency	MHz	470 - 790
Gain	dB	III+DAB: 33; IV: 31; V: 31; UHF: 31
Gain adjustment	dB	III+DAB: 20; IV: 20; V: 20; UHF: 20
Optical noise figure	dB	FM: 4.5; III+DAB: 4.5; UHF: 7.5
Outputs number		1
Output level	dB μ V	III+DAB: 122; UHF: 125
Connectors		F female

Specifications		
Power supply voltage	Vdc/A	220-230 / 50-60
Current consumption	W	8.5
Isolation class		II
Remote feeding		100mA@12V total
Output test	dB	-30
Impedence	Ω	75
Operating temperature	°C	-10 to +55
Protection		IP20
Dimensions and packaging		
Pieces		1
EAN code		8016978094578
Packaging dimensions	mm	240 x 190 x 60
Product dimensions	mm	194 x 143 x 64
Packaging weight	kg	1.7
Net Weight	kg	2.1
Weight	kg	2.2