

INSDC3A

Power supply



Power inserter with **female F-connectors**, maximum current pass 3A.

Technical Chars

- It is used to **supply power to SCD2 multiswitches in cascade**; passing current between the ports of the multiswitches also allows the LNBs to be powered. Also suitable to insert power wherever required in a distribution system.
- Can be used with any type of power supply e.g. PSU1430F or PSU1830F.
- **Low insertion loss.**
- Passes terrestrial and satellite (**40MHz - 2400MHz**).
- Compact size.

initial_fields		
Code		287612
Inputs		1 SAT, TV
Outputs		1 SAT, TV
Bandwidth	MHz	40-2400
Insertion loss	dB	0.5
Max current	mA	3000
Connector		F x3
Specifications		
Operating temperature	°C	-10 to +55
Dimensions and packaging		
Pieces		1
EAN code		8016978105922
Packaging dimensions	mm	50 x 50 x 24.5
Product dimensions	mm	50 x 50 x 17
Packaging weight	Kg	0.046