

ALPHA5+ LTE700



5 elements **UHF band Loop Yagi** aerial complete with F connector and tube reflector.

- **No tool needs for mounting** ALPHA series, thanks to premounted elements, quick coupling radiator and reflectors and mast bracket with zenith adjustment and **wingnut**.
- **5G and 4G LTE filter** inserted in the radiator dipole.
- Excellent gain, impedance matching and **directivity**.
- Exclusive design **patented** by Fracarro.

CODE	213225	
Elements	no.	5
Band		UHF
Channel		E21-E48
Bandwidth	MHz	470-694
Gain	dBi	14.2
Front/Back ratio	dB	38
Return loss	dB	-18
Beamwidth (-3dB)	°	±22
Wind load at 120km/h (720N/m ²)	kg (N)	7.7 (75.46)
Connector	Type	F
Impedance	Ω	75
Max mast (Ø)	mm	60
Dimensions (L x H)	cm	81 x 58
Quantity Masterbox	pcs	12
Unit weight	kg	1.70
Total weight	kg	23.1

Accessories

Horizontal polarization	Included
Horizontal polarization Tilt adjustment	Included
Vertical polarization	Included
Vertical polarization Tilt adjustment	Included
Auxiliary boom	N.P.