



AFI313T

3-input (FM, III+DAB, UHF) indoor amplifier with 30dB gain and up to **110dB μ V output level on UHF band**, independent level adjustment (15dB) for each input and low noise figure.

- Indoor amplifier with **F connector** to amplify and distribute DVB/T-T2 and DVB/S-S2 signals on residential buildings, houses or flats.
- Switching power supply, low power consumption.
- **Built-in screwdriver to adjust gain and slope.**
- Under cover adjustment.
- Hidden wall mount screws.
- Green led - power on.

CODE	223236	
Input no.	3 (con regolazioni separate)	
Band	FM, III+DAB, UHF	
Outputs	1	
Output level	(dB μ V)	118
Gain	(dB)	25, 25, 30
Adjustment	(dB)	15, 15, 15
Noise figure	(dB)	4.5, 4.5, 4.5
Pieces	1	