

## ANT1200A

FM and DAB



FM band aerial complete with F connector. Different design for the radio signals reception.

### Technical Chars

ANT1200A		
Code		213001
Elements		1
Band		FM
Bandwidth	MHz	87.5-108
Gain	dBi	2.1
Front/Back ratio	dB	Omn
Return loss	dB	-16
Beam width (3dB)	°	360
Wind load 120Km/h 729N/m <sup>2</sup>	Kg (N)	3.0 (29.4)
Connector		F
Impedence	Ohm	75
Max mast diameter	mm	60
Dimensions	cm	96 x 77
Accessories		
Horizontal polarization		Included
Horizontal polarization tilt adjustment		-
Vertical polarization		-
Auxiliary boom		-
Dimensions and packaging		
Pieces		10
EAN code		8016978061556
Multiple EAN		8016978062997
Packaging dimensions	mm	450 x 330 x 880

Packaging weight	Kg	8.6
Unit weight	Kg	0.90
Total weight	Kg	10.6

Gain (x: MHz frequency, y: ISO dBi gain) and Polar diagram (@105MHz for ANT1200A and FMOMNI, @230MHz for DAB)

