


SIGMA V2 HD

VHF



Loop Yagi band III aerial complete with F connector. No tool needs for mounting thanks to its quick coupling radiator, reflector and director elements. Exclusive design patented by Fracarro.

Technical Chars

- Equipped with **two special circular directing elements** and a curtain reflector for high electrical performance while maintaining a short length.
- Radiator dipole and **quick-connect elements** on a slide already present on the cradle; assembly is completed **without the need for any tools**.
- Exclusive **Sigma design** patented by Fracarro.

SIGMA V2 HD		
Code		213203
Elements		2
Band		3
Channel		E5-E12
Bandwidth	MHz	174-230
Gain	dBi	11.5
Front/Back ratio	dB	25
Return loss	dB	-12
Beam width (3dB)	°	±25
Wind load 120Km/h 729N/m²	Kg (N)	10 (98.1)
Connector		F
Impedence	Ohm	75
Max mast diameter	mm	60
Dimensions	cm	76 x 100
Accessories		
Horizontal polarization		Including
Horizontal polarization tilt adjustment		Including
Vertical polarization		Including
Vertical polarization tilt adjustment		Including
Auxiliary boom		N.P.