

MBJ2557

Multiband amplifier



Multiband TV indoor amplifier of the MBJ line to amplify and mix signals from one or more aerials; with F connectors, separate amplification and independent level adjustment for each input and low noise figure.

initial_fields		
Code		223300
Input no.		4
Inputs		FM, III+DAB, UHF, UHF, SAT
Frequency FM	MHz	88 - 108
DAB, III Frequency	MHz	174 - 250
Frequency	MHz	470 - 862
Frequency	MHz	950-2150
Gain	dB	FM: 28; III+DAB: 28; UHF: 26; UHF: 26; SAT: 33-38 (sloped)
Gain adjustment	dB	FM: 20; III+DAB: 20; UHF: 20; UHF: 20; SAT: 20
Optical noise figure	dB	FM: 5; III+DAB: 5; UHF: 7; SAT: 6
Outputs number		1
Output level	dB μ V	FM: 109; III+DAB: 116; UHF: 119; SAT: 110
Connectors		F female
Specifications		
Power supply voltage	Vdc/A	220-230 / 50-60
Current consumption	W	5
Remote feeding		100mA@12V total
Operating temperature	°C	-10 to +55
Dimensions and packaging		
EAN code		8016978087747
Product dimensions	mm	127 x 58 x 128