


## MBJ2r345U LTE/..

Multiband amplifier



4-input (III+DAB, IV, V, UHF) multiband TV indoor amplifier with 20dB gain and up to 115dBμV output level on UHF band, separate amplification with independent level adjustment (20dB) for each input and low noise figure. Version available with special tuning on the cut between band IV and V and 790MHz 4G LTE integrated filter.

### Technical Chars

- **Special settings model:** it is necessary to specify the last RF channel in B4 and the first channel in B5 during the order process; on standard models, B4 includes channels from E21 to E35 and B5 includes channels from E36 to E48.

initial_fields		
Code		223604
Input no.		4
Inputs		III+DAB, IV, V, UHF (*)
Specifications		
Power supply voltage	Vdc/A	220-230 / 50-60
Current consumption	W	5
Dimensions and packaging		
Pieces		1
EAN code		8016978100002
Packaging dimensions	mm	152 x 105 x 47
Packaging weight	kg	0.345