

MBJ2rFM+3UU LTE

Multiband amplifier



3-input (FM+III+DAB, UHF, UHF) multiband TV indoor amplifier with 20dB gain and up to 115dB μ V output level on UHF band, separate amplification with independent level adjustment (20dB) for each input and low noise figure. 790MHz 4G LTE integrated filter.

Technical Chars

- **A.B.L.A. functionality.** FRACARRO's exclusive system for maintaining the set output level constant even when the level of each input changes (independent A.B.L.A. circuits) with **output level stabilisation** even for high variations in the input TV signal and **LED operation** of the dedicated A.B.L.A. circuits.
- **High shielding** against LTE interference (LTE Free)
- Protective shell: the new switchboards are equipped with an ABS fireproof and flame retardant (Class V0) enclosure
- Prepared for **mounting** on a standard **DIN rail** with quick release.
- The dimensions of the MBJ EVO T2 have been designed so that they can be easily installed inside wall boxes.
- **Very high efficiency switching power supply** (>80%) and self-resetting **short-circuit protection** circuit.
- Selector for **remote power supply** on each input (100mA total).
- Power supply status LED.
- Faston for connection to TV system earth.

initial_fields		
Code		223611
Input no.		3
Inputs		FM+III+DAB, UHF, UHF
Frequency FM	MHz	88 - 108
DAB, III Frequency	MHz	174 - 230
Frequency	MHz	470 - 790
Gain	dB	FM+III+DAB: 20; UHF: 20; UHF: 20
Gain adjustment	dB	FM+III+DAB: 20; UHF: 20; UHF: 20
Optical noise figure	dB	FM+III+DAB: 6; UHF: 9
Outputs number		1
Output level	dB μ V	III+DAB: 110; UHF: 115
Connectors		F female

Specifications		
Power supply voltage	Vdc/A	220-230 / 50-60
Current consumption	W	5
Isolation class		II
Remote feeding		100mA@12V total
Operating temperature	°C	-10 to +55
Protection		IP20
Conformity		EN62368-1:2014/AC:2015; EN50083-2:2012/A1:2015
Dimensions and packaging		
Pieces		1
EAN code		8016978099863
Packaging dimensions	mm	152 x 105 x 47
Product dimensions	mm	135 x 82 x 39
Packaging weight	kg	0.345
Weight	kg	0.34