

## KW35D

## K Series



Wideband amplifiers with push-pull technology capable of amplifying the entire 47-862 MHz band. Equipped with one input and one output, they are used to amplify the signal coming from a KF filter battery or other modules (receivers, modulators, etc.).

The KW35E model allows the passive return channel 5-30 MHz.

KW35D		
Code		270061
Connectors		F
Input frequency	MHz	47-862
Gain	dB	35
Gain adjustment	dB	20
Slope	dB	0-20
Max power	dB $\mu$ V	125
Noise	dB	5
Return loss	dB	10
Impedence	Ohm	75
Power supply voltage	V	12
Operating temperature	$^{\circ}$ C	-10 to +55
Dimensions and packaging		
Pieces		1
EAN code		8016978074631
Packaging dimensions	mm	198 x 140 x 62
Product dimensions	mm	63 x 184 x 107
Packaging weight	Kg	0.718